

## Analog Input RTD

Input Channels	6
Input Type	RTD
Wire connection	2/3 wire
RTD Type	Pt100, Pt1000, Ni120, Cu100, Cu1000
Resolution	16-bit
Sampling Rate	12 samples/ second (Total)
Accuracy	+/-0.05%
-3dB BandWidth	15.7Hz
Zero drift	+/-0.5 $\mu$ V/ $^{\circ}$ C
Span drift	+/-20 $\mu$ V/ $^{\circ}$ C
Common Mode Rejection	150 dB
Normal Mode Rejection	100 dB
Voltage Input Impedance	>1M Ohms
Open Wire Detection	Yes
Individual Channel Configurable	Yes
3-wire RTD long distance measurement	Yes
ESD Protection	4KV Contact for each terminal 8KV Air for random point
EFT Protection	4KV to Power, and 1KV to RS-485
Intra-module Isolation, Field to Logic	3000 VDC
<b>Interface</b>	
Interface	RS-485
Format	N, 8, 1
Baud Rate	1200 ~ 115200bps
<b>LED Display</b>	
1 LED as Power/ Communication indicator	
<b>Power</b>	
Input	+10 to +30 Vdc
Power Consumption	1.2W
<b>Environment</b>	
Operating temperature	-25 to 75 $^{\circ}$ C
Storage temperature	-40 to 85 $^{\circ}$ C
Humidity	5 to 95%, non-condensing



### i-7015P

6-channel RTD Input Module

Type Code	RTD Type	Temperature Range $^{\circ}$ C
20	Platinum 100, a= 0.00385	-100 ~ 100
21	Platinum 100, a= 0.00385	0 ~ 100
22	Platinum 100, a= 0.00385	0 ~ 200
23	Platinum 100, a= 0.00385	0 ~ 600
24	Platinum 100, a= 0.003916	-100 ~ 100
25	Platinum 100, a= 0.003916	0 ~ 100
26	Platinum 100, a= 0.003916	0 ~ 200
27	Platinum 100, a= 0.003916	0 ~ 600
28	Nickel 120	-80 ~ 100
29	Nickel 120	0 ~ 100
2A	Platinum 1000, a = 0.00385	-200 ~ 600
2E	PT 100, a= 0.00385	-200 $^{\circ}$ C ~ +200 $^{\circ}$ C
2F	PT 100, a= 0.003916	-200 $^{\circ}$ C ~ +200 $^{\circ}$ C
80	PT 100, a= 0.00385	-200 $^{\circ}$ C ~ +600 $^{\circ}$ C
81	PT 100, a= 0.003916	-200 $^{\circ}$ C ~ +600 $^{\circ}$ C

## Industrial Weighing Systems

9 Richmond St. Picton, ON Canada K0K 2T0

Ph: 613-786-0016 Cell/Local: 613-921-0397 Fax: 613-476-5293

E-mail [info@iwsystems.ca](mailto:info@iwsystems.ca) Website: [www.iwsystems.ca](http://www.iwsystems.ca)